

X-BAND AIR

Avionic Crossband Repeater

BRIDGING THE GAP BETWEEN AIR AND LAND



19" Rack with F5021 & A120

Communication just got easier with the X-Band Air repeater. Icom's avionic crossband repeater provides fast, seamless communications between VHF/FM, UHF/FM, AM and air band frequencies. The X-Band Air provides interoperability between ground crew and air crew for forestry, hospitals and oil rigs.

The repeater features full VFO capability in one box. The compact size allows for flexible configurations. Set the X-Band air on a desktop, put it in a case that can be used anywhere or mount in a 19" industry standard rack frame.

Powerful Crossband Capability - Fast and Responsive, from Air to Ground in Seconds

- · Versions: AIR BAND + VHF, or AIR BAND + UHF
- Output Power: 50 Watts VHF; 45 Watts UHF; 36 Watts Peak AIR BAND
- Local controlled operation; can also be used as a dual base unit (with optional mic)

Size and Feature Set Flexibility

 Mount in a 19" rack, a desktop configuration or placed in a RDS case, depending on your needs

Maximum Frequency Flexibility— Alpha Tag Your Channels

- VHF & UHF Land Mobile
 128 Memory channels with 8 memory banks per radio
- 8 Character alphanumeric display/easy to read
- Air Band: 200 memory channels w/ 12 character channel names Easy to read alphanumeric characters and icons

Battery Backup

Configurable to 120V or 220V AC input.
 Can switch over to customer-supplied 12 volt DC battery backup if AC power fails.



When you need to have air support

AVIONIC CROSSBAND REPEATER

X-BAND AIR

ADDITIONAL FEATURES

- Automatic battery backup charging system
- Internal controller with programmable Hang Timer
- DB25 accessory connector with EPTT, COR, DISC, EMOD and AFO for each radio
- Built-in AC EMI filter

SPECIFICATIONS

if you need 25kHz bandwidth
**Depends on configuration

GENERAL			
Frequency coverage	: AIR	118.0-136.992MHz	
	: VHF	136-174MHz	
	: UHF	440-470MHz	
Number of channels	: AIR	200 channels	
	:VHF/UHF	128 channels/8 zones	
Channel spacing	: AIR	25kHz/8.33kHz	
	: VHF/UHF	12.5/25kHz / 15/30kHz*	
PLL channel step	: VHF/UHF	2.5, 3.125kHz	
Frequency stability	: AIR	±5.0 ppm	
	: VHF/UHF	±2.5 ppm	
Operating temp. range	: -30°C to +60°C; -22°F to +140°F		
Power supply voltage	: 13.6 V DC		
Current drain (approx.)	: AIR	TX: 5.0A (maximum)	
, , ,		RX: 4.0A (at AF max.), 0.5A (at standy-by)	
	: VHF	TX: 10A (at 50W/45W approx.)	
		RX: 0.7 A/250mA (Max. audio/stand-by)	
	: UHF	TX: 11A (at 50W/45W approx.)	
	==== (====	RX: 0.7 A/250mA (Max. audio/stand-by)	
Antenna impedance	: 50Ω (SO-2	50Ω (SO-239)	
Dimensions (WxHxD)**	: 482.6 x 127 x 393.7mm		
	19" x 5" x 15.5"		
Weight**	: 8.6kg; 19 lbs		
*25kHz bandwidth is no longer available for FCC Part 90 licenses for USA versions. Ask your dealer			

OPTIONS MICROPHONES:











Supplied Accessories

AC Power Cord

BACK VIEW

110V outlet.

• DC Power Cord

A clean rear panel design allows for easy setup and operation.

An options connector allows for customized applications such as Inter-

connect, CWID, and more. A standard PC-type power cord plugs into a

Contact Icom America for more information:

Output power : AIR 9W (Carrier power) typical : VHF 50W

: UHF 45W

Max. frequency deviation : VHF/UHF ±5.0/±2.5 kHz (wide/narrow)

Spurious emission : AIR Less than -60 dBc

TRANSMITTER

: VHF/UHF 70 dB typ. : 70/60dB (wide/narrow)

 $\begin{array}{ll} \mbox{Adjacent Ch. power} & : 70/60dB \mbox{ (wide/narrow)} \\ \mbox{Mic. impedence} & : 600\Omega \mbox{ (8-pin modular)} \end{array}$

RECEIVER

Sensitivity : AIR <1 μ V typ. (6db S/N)

: VHF/UHF $0.25 \,\mu\text{V}$ typ. (at 12dB SINAD)

Squelch sensitivity : AIR ${\rm < 0.35~\mu V~(pd)}$

: VHF/UHF $0.25 \,\mu\text{V}$ typ.

Adjacent ch. selectivity : AIR 6dB/60dB

: VHF/UHF 75/65dB typ. (wide/narrow) : AIR > 74dBµ

Spurious response : AIR > 74dBµ

: VHF/UHF 80dB

Intermodulation (typical) : VHF/UHF 75dB typ.

Audio output power : AIR 1.5W typical at 10% distortion with an internal SP (8 Ω load)

: VHF/UHF 4W typical at 10% distortion

with an internal SP (4Ω load)

External SP connector : 2-conductor 3.5 (d) mm $(^{1}/_{8}")/4\Omega$



INSIDE VIEW

systems@icomamerica.com

www.icomamerica.com

Icom America Inc. 12421 Willows Road NE Kirkland WA 98034

800-872-4266

GSA contract #GS-35F-0109L

